

nERGY

400 Series Remote Siren with Knob Control
100 and 200 Watts



Remote

100 Watts
200 Watts

ETSA481RSR
ETSA482RSR

Note: 2 speakers required with the 200 watt version

Features

- > Hands free feature allow siren tones to be cycled or cancelled by pressing horn (horn-ring circuit must be connected)
- > Removable microphone with quarter inch plug
- > Designed with extra large buttons with appropriate spacing to eliminate buttons to be accidentally pressed
- > Provides up to eight 10 amps and three 20 amp outputs with internal fuses for powering solenoids (i.e. gunlock) or supplying power and signaling to other onboard peripherals (printer, radar, GPS, etc.)
- > Built-in protection against over/under voltage, short circuit and reverse polarity
- > Officers value the sound intensity of the dual-tone feature "fooling" perpetrators into believing multiple police vehicles are in pursuit
- > 200 watt sirens feature dual-tone capability to deliver two siren tones at once to provide officers with extreme "traffic moving" capability

Technical Specifications

WATTS	100 and 200 Watts (2 speakers required with the 200 watt version)
INPUT VOLTAGE	10-16 Vdc
DIMENSIONS	
Handheld	Panel: 3.51" (8.92 cm) H x 6.98" (17.73 cm) W x 1.17" (2.98 cm) D
Remote	Amplifier/Relay: 2.62" (6.66 cm) H x 7" (17.80 cm) W x 6.51" (16.54 cm) D
CERTIFICATIONS	Meets or exceeds SAE J1849 and CA Title 13 sound levels when used with SoundOff Signal® speakers
WARRANTY	Three-year